



contents

Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-001-1.0	15A/100 Ω	10A/100 Ω	1000:1	7.5	23.4	11.11	0~200KHZ
CT-002-2.0	54A/100 Ω	20A/100 Ω	2000:1	7.5	23.4	11.11	0~200KHZ
CT-002B-2.0	30A/100 Ω	20A/100 Ω	2000:1	7.5	23.4	11.11	0~200KHZ
CT-002Z-1.0	60A/100 Ω	30A/100 Ω	1000:1	7.5	23.4	11.11	50~60HZ
CT-003-1.0	45A/100 Ω	10A/100 Ω	1000:1	7.0	23.5	11.25	0~200KHZ
CT-005-2.0	56A/100 Ω	32A/100 Ω	2000:1	6.5	24.0	11.00	0~200KHZ
CT-005-2.5	75A/100 Ω	40A/100 Ω	2500:1	6.5	24.0	11.00	0~200KHZ
PT-006-1.0/1.0	1mA/1mA	1mA/1mA	1000:1000	19.5	17.2	10.2	0~200KHZ
CT-007-1.0/1.0	2mA/1mA	2mA/2mA	1000:1000	19.8	16.7	17.30	0~200KHZ
CT-008-1.0	42A/100 Ω	20A/100 Ω	1000:1	8.7	26.5	17.00	0~200KHZ
CT-008-2.0	87A/100 Ω	40A/100 Ω	2000:1	8.7	26.5	17.00	0~200KHZ
CT-008-2.5	100A/100 Ω	50A/100 Ω	2500:1	8.7	26.5	17.00	0~200KHZ
CT-008-3.0	120A/100 Ω	50A/100 Ω	3000:1	8.7	26.5	17.00	0~200KHZ
CT-009-0.5	30mA/1k Ω	30mA/1k Ω	500:1	10.2	24.00	10.00	50~60HZ
CT-009-1.0	16A/100 Ω	10A/100 Ω	1000:1	10.2	24.00	10.00	0~200KHZ
CT-009-2.0	40A/100 Ω	10A/100 Ω	2000:1	10.2	24.00	10.00	0~200KHZ
CT-010-1.5/15	10mA/10mA	10mA/10mA	1500:1500	6.00	26.90	18.40	0~200KHZ
CT-011-	40A/100 Ω	32A/100 Ω	2000:1	3.00	32.70	25.5	0~200KHZ
10:500:2.0	30mA/1k Ω	30mA/1k Ω	500:1	10.2	24.00	10.00	50~60HZ
CT-012-1.0	45A/100 Ω	20A/100 Ω	1000:1	11.0	28.0	16.5	0~200KHZ
CT-012-2.0	90A/100 Ω	40A/100 Ω	2000:1	11.0	28.0	16.5	0~200KHZ
CT-013-0.3	1A/100 Ω	1A/100 Ω	300:1	5.8	15.00	21.00	0~200KHZ
CT-014-0.5	30mA/1k Ω	30mA/1k Ω	500:1	8.3	24.00	10.00	50~60HZ
CT-014-1.0	20A/100 Ω	10A/100 Ω	1000:1	8.3	24.00	10.00	0~200KHZ
CT-014-3.6	36A/100 Ω	20A/100 Ω	3600:1	8.3	24.00	10.00	0~200KHZ
CT-015Z-1.0	60A/100 Ω	30A/100 Ω	1000:1	17.55	29.5	13.5	50~60HZ
CT-017-0.5	30mA/1k Ω	30mA/1k Ω	500:1	14.5	31.8	9.20	0~200KHZ
CT-017-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.5	31.8	9.20	0~200KHZ
CT-017-1.0	13A/100 Ω	10A/100 Ω	1000:1	14.5	31.8	9.20	0~200KHZ
CT-017Z-1.0	45A/100 Ω	40A/100 Ω	1000:1	14.5	31.8	9.20	50~60HZ
CT-018Z-1.0	270A/100 Ω	100A/100 Ω	1000:1	26.2	45.00	20.00	50~60HZ
CT-019Z-1.0	270A/100 Ω	100A/100 Ω	1000:1	17.00	28.00	13.50	50~60HZ
CT-020-2.0*3	200A/100 Ω	100A/100 Ω	2000:1	9.6	87.00	23.00	0~200KHZ



contents

Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-023-2.0	75A/100 Ω	30A/100 Ω	2000:1	5.60	20.9	15.60	0~200KHZ
CT-026Z-1.0	200A/100 Ω	100A/100 Ω	1000:1	20.00	44.5	25.00	50~60HZ
CT-026Z-2.0	400A/100 Ω	200A/100 Ω	2000:1	20.00	44.5	25.00	50~60HZ
CT-026Z-4.0	800A/100 Ω	400A/100 Ω	4000:1	20.00	44.5	25.00	50~60HZ
CT-028Z-2.0	200A/100 Ω	100A/100 Ω	2000:1	19.00	39.00	15.00	50~60HZ
CT-029-2.2	30mA/1k Ω	30mA/1k Ω	2200:1	31.8	50.6	11.00	0~200KHZ
CT-030Z-2.0	400A/100 Ω	200A/100 Ω	2000:1	27.00	44.8	15.38	50~60HZ
CT-032-2.0*2	400A/100 Ω	200A/100 Ω	2000:1	35.00	64.8	23.60	50~60HZ
CT-032D-2.0	400A/100 Ω	200A/100 Ω	2000:1	37.10	54.00	14.07	50~60HZ
CT-032D-4.0	800A/100 Ω	400A/100 Ω	4000:1	37.10	54.00	14.07	50~60HZ
CT-033-1.0*2	100A/100 Ω	40A/100 Ω	1000:1	8.80	44.4	21.50	50~60HZ
CT-034-1.0	36A/100 Ω	20A/100 Ω	2000:1	4.90	18.30	20.00	0~200KHZ
CT-034-2.0	36A/100 Ω	20A/100 Ω	2000:1	4.90	18.30	20.00	0~200KHZ
CT-037-2.0	60A/100 Ω	32A/100 Ω	2000:1	6.70	23.60	26.50	0~200KHZ
CT-037U-2.0	60A/100 Ω	32A/100 Ω	2000:1	6.70	23.60	26.50	0~200KHZ
CT-038-2.0*2	800A/100 Ω	400A/100 Ω	4000:1	35.00	64.8	23.60	50~60HZ
CT-039Z-2.0	400A/100 Ω	200A/100 Ω	2000:1	25.00	41.00	31.60	50~60HZ
CT-039Z-4.0	800A/100 Ω	400A/100 Ω	4000:1	25.00	41.00	31.60	50~60HZ
CT-045Z-7.50	2000A/100 Ω	1000A/100 Ω	7500:1	49.80	94.70	40.50	50~60HZ
CT-050-2.0	36A/100 Ω	20A/100 Ω	2000:1	7.70	16.00	17.60	0~200KHZ
CT-051-0.5	30mA/1k Ω	30mA/1k Ω	500:1	8.00	26.20	13.60	0~200KHZ
CT-051-1.0	36A/100 Ω	20A/100 Ω	1000:1	8.00	26.20	13.60	0~200KHZ
CT-051-2.0	78A/100 Ω	32A/100 Ω	2000:1	8.00	26.20	13.60	0~200KHZ
CT-052-0.5	30mA/1k Ω	30mA/1k Ω	500:1	11.50	28.80	16.40	0~200KHZ
CT-052-2.0	33A/100 Ω	20A/100 Ω	1000:1	11.50	28.80	16.40	0~200KHZ
CT-052-2.0	94A/100 Ω	50A/100 Ω	2000:1	11.50	28.80	16.40	0~200KHZ
CT-052Z-2.5	400A/100 Ω	200A/100 Ω	2500:1	11.50	28.80	16.40	0~200KHZ
CT-055-1.0	36A/100 Ω	20A/100 Ω	1000:1	6.80	19.00	11.60	0~200KHZ
CT-055H-1.8	45A/100 Ω	32A/100 Ω	1800:1	6.80	19.00	11.60	0~200KHZ
CT-055H-2.0	62A/100 Ω	32A/100 Ω	2000:1	6.80	19.00	11.60	0~200KHZ
CT-055V-2.0	62A/100 Ω	32A/100 Ω	2000:1	6.80	19.00	11.60	0~200KHZ
CT-055H-2.5	62A/100 Ω	32A/100 Ω	2500:1	6.80	19.00	11.60	0~200KHZ
CT-056-1.0	30A/100 Ω	20A/100 Ω	1000:1	6.70	23.35	13.30	0~200KHZ
CT-056-2.0	56A/100 Ω	32A/100 Ω	2000:1	6.70	23.35	13.30	0~200KHZ



contents

Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-057-1.0	22A/100 Ω	10A/100 Ω	1000:1	9.30	24.30	12.50	0~200KHZ
CT-057-2.0	90A/100 Ω	50A/100 Ω	2000:1	9.30	24.30	12.50	0~200KHZ
CT-057L-2.0	90A/100 Ω	50A/100 Ω	2000:1	9.30	24.30	12.50	0~200KHZ
CT-059Z-2.0	400A/100 Ω	200A/100 Ω	2000:1	17.00	28.00	20.00	50~60HZ
CT-060Z-2.0	1000A/100 Ω	600A/100 Ω	2000:1	57.00	74.50	17.20	50~60HZ
CT-060Z-3.0	1500A/100 Ω	800A/100 Ω	3000:1	57.00	74.50	17.20	50~60HZ
CT-060Z-4.0	2000A/100 Ω	1000A/100 Ω	4000:1	57.00	74.50	17.20	50~60HZ
CT-061Z-2.0	1000A/100 Ω	600A/100 Ω	2000:1	31.00	47.50	28.00	50~60HZ
CT-061Z-3.0	1500A/100 Ω	900A/100 Ω	3000:1	31.00	47.50	28.00	50~60HZ
CT-061Z-4.0	2000A/100 Ω	1200A/100 Ω	4000:1	31.00	47.50	28.00	50~60HZ
CT-062-2.0	137A/100 Ω	60A/100 Ω	2000:1	12.60	36.00	18.30	0~200KHZ
CT-063-2.0*3	110A/100 Ω	50A/100 Ω	2000:1	9.10	34.00	23.50	0~200KHZ
CT-064-0.8	40A/100 Ω	20A/100 Ω	800:1	8.20	30.50	17.40	0~200KHZ
CT-064-1.0	48A/100 Ω	32A/100 Ω	1000:1	8.20	30.50	17.40	0~200KHZ
CT-064-2.0	135A/100 Ω	60A/100 Ω	2000:1	8.20	30.50	17.40	0~200KHZ
CT-068-1.0	100A/100 Ω	60A/100 Ω	1000:1	11.7	35.50	22.00	0~200KHZ
CT-068-2.0	200A/100 Ω	100A/100 Ω	2000:1	11.7	35.50	22.00	0~200KHZ
CT-069-1.0	33A/100 Ω	20A/100 Ω	1000:1	8.0	26.00	15.00	0~200KHZ
CT-069-2.0	85A/100 Ω	40A/100 Ω	2000:1	8.0	26.00	15.00	0~200KHZ
CT-070-0.5	30mA/1k Ω	30mA/1k Ω	500:1	19.4	40.40	14.50	0~200KHZ
CT-070-2.0	120A/100 Ω	100A/100 Ω	2000:1	19.4	40.40	14.50	0~200KHZ
CT-070-3.0	200A/100 Ω	150A/100 Ω	3000:1	19.4	40.40	14.50	0~200KHZ
CT-070Z-1.0	250A/100 Ω	120A/100 Ω	1000:1	19.4	40.40	14.50	50~60HZ
CT-070Z-2.5	500A/100 Ω	300A/100 Ω	2500:1	19.4	40.40	14.50	50~60HZ
CT-073B-2.0	138A/100 Ω	100A/100 Ω	2000:1	19.4*3.0	40.40	13.70	0~200KHZ
CT-082-0.1	1.0A/10 Ω	1.0A/10 Ω	100:1	5.00	18.30	10.12	0~200KHZ
CT-082-0.2	2.0A/10 Ω	2.0A/10 Ω	200:1	5.00	18.30	10.12	0~200KHZ
CT-082-0.3	3.0A/10 Ω	3.0A/10 Ω	300:1	5.00	18.30	10.12	0~200KHZ
CT-082-0.5	5.0A/10 Ω	5.0A/10 Ω	500:1	5.00	18.30	10.12	0~200KHZ
CT-082-0.6	6.0A/10 Ω	6.0A/10 Ω	600:1	5.00	18.30	10.12	0~200KHZ
CT-082-1.0	11A/10 Ω	5.0A/10 Ω	1000:1	5.00	18.30	10.12	0~200KHZ
CT-082-2.0	36A/10 Ω	10A/10 Ω	2000:1	5.00	18.30	10.12	0~200KHZ
CT-082D-1.0	25A/10 Ω	16A/10 Ω	1000:1	1.80	15.80	13.50	0~200KHZ
CT-082G-2.0	100A/3.3 Ω	100A/3.3 Ω	2000:1	4.60	18.80	11.80	0~200KHZ



contents

Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-082K-2.0	30A/100 Ω	16A/100 Ω	2000:1	2.30	18.0	15.70	0~200KHZ
CT-082TU-0.1	30A/10 Ω	16A/10 Ω	100:1	2.30	18.2	10.00	10K~70KHZ
CT-082TU-0.2	40A/10 Ω	25A/10 Ω	200:1	2.30	18.2	10.00	10K~70KHZ
CT-082TU-0.3	50A/10 Ω	30A/10 Ω	300:1	2.30	18.2	10.00	10K~70KHZ
CT-083-1.0	105A/50 Ω	50A/50 Ω	1000:1	26.00	45.80	18.10	0~200KHZ
CT-083-1.0	105A/50 Ω	50A/50 Ω	1000:1	26.00	45.80	18.10	0~200KHZ
CT-083-1.5	135A/50 Ω	60A/50 Ω	1500:1	26.00	45.80	18.10	0~200KHZ
CT-083-2.0	150A/50 Ω	80A/50 Ω	2000:1	26.00	45.80	18.10	0~200KHZ
CT-083Z-2.0	600A/100 Ω	200A/100 Ω	2000:1	26.00	45.80	18.10	50~60HZ
CT-084-2.0NZ	95A/50 Ω	50A/50 Ω	2000:1	24.00	45.80	20.00	10K~70KHZ
CT-085Z-1.0	150A/100 Ω	100A/100 Ω	1000:1	10.3	34.62	18.80	50~60HZ
CT-085Z-2.0	200A/100 Ω	150A/100 Ω	2000:1	10.3	34.62	18.80	50~60HZ
CT-086-0.5F	24A/50 Ω	10A/50 Ω	500:1	24.00	57.00	23.60	10K~200KHZ
CT-086-2.0F	130A/100 Ω	70A/100 Ω	2000:1	24.00	57.00	23.60	10K~200KHZ
CT-086-3.0F	165A/100 Ω	100A/100 Ω	3000:1	24.00	57.00	23.60	10K~200KHZ
CT-087-1.0	25A/10 Ω	16A/10 Ω	1000:1	1.80	15.80	18.00	0~200KHZ
CT-090Z-1.0	150A/100 Ω	100A/100 Ω	1000:1	14.00	35.00	14.60	50~60HZ
CT-090Z-2.0	200A/100 Ω	150A/100 Ω	2000:1	14.00	35.00	14.60	50~60HZ
CT-090Z-3.0	300A/100 Ω	200A/100 Ω	3000:1	14.00	35.00	14.60	50~60HZ
CT-092Z-1.0	400A/100 Ω	200A/100 Ω	1000:1	30.60	58.30	19.20	50~60HZ
CT-092Z-2.0	600A/100 Ω	300A/100 Ω	2000:1	30.60	58.30	19.20	50~60HZ
CT-092-4.0	600A/100 Ω	300A/100 Ω	4000:1	30.60	58.30	19.20	0~200KHZ
CT-093Z-2.0	600A/100 Ω	300A/100 Ω	2000:1	19.4	54.9	17.50	50~60HZ
CT-093Z-2.5	750A/100 Ω	400A/100 Ω	2500:1	19.4	54.9	17.50	50~60HZ
CT-095-2.0	85A/100 Ω	50A/100 Ω	2000:1	9.40	24.00	11.70	0~200KHZ
CT-095Z-1.0	40A/100 Ω	20A/100 Ω	1000:1	9.40	24.00	11.70	50~60HZ
CT-095Z-2.0	80A/100 Ω	40A/100 Ω	2000:1	9.40	24.00	11.70	50~60HZ
CT-095Z-2.5	98A/100 Ω	50A/100 Ω	2500:1	9.40	24.00	11.70	50~60HZ
CT-095Z-3.0	200A/100 Ω	100A/100 Ω	3000:1	9.40	24.00	11.70	50~60HZ
CT-096-4.0	180A/100 Ω	100A/100 Ω	4000:1	20.00	48.60	18.30	0~200KHZ
CT-096Z-1.0	300A/100 Ω	200A/100 Ω	1000:1	20.00	48.60	18.30	50~60HZ
CT-096Z-2.0	400A/100 Ω	300A/100 Ω	2000:1	20.00	48.60	18.30	50~60HZ
CT-097-2.0	85A/100 Ω	50A/100 Ω	2000:1				0~200KHZ
CT-098-1.0/1.0	10mA/10mA	10mA/10mA	1000:1000				0~200KHZ



contents

Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-100Z-2.0	500A/100 Ω	300A/100 Ω	2000:1	20.30	52.00	28.00	50~60HZ
CT-103Z-4.0	1000A/100 Ω	500A/100 Ω	4000:1	34.60	98.80	89.83	50~60HZ
CT-105Z-2.5	1000A/100 Ω	500A/100 Ω	2500:1	44.50	100.7	33.00	50~60HZ
CT-110-0.1*2	5A/100 Ω	1A/100 Ω	100:1	8.80	44.4	21.50	50~60HZ
CT-120-0.65	30mA/1k Ω	30mA/1k Ω	650:1	6.00	17.50	8.60	0~200KHZ
CT-130L-2.0	78A/100 Ω	32A/100 Ω	2000:1	9.80	25.14	11.50	0~200KHZ
CT-131L-2.5	93A/100 Ω	60A/100 Ω	2500:1	12.00	37.70	14.00	0~200KHZ
CT-132-0.47	10A/10 Ω	8A/10 Ω	470:1	1.20	25.18	10.00	10K~70KHZ
CT-133-0.20	10A/10 Ω	8A/10 Ω	200:1	2.00	16.50	6.35	10K~70KHZ
CT-134-1.0*3	50A/100 Ω	30A/100 Ω	1000:1	10.00	101.00	28.00	0~200KHZ
CT-135-2.0*3	80A/100 Ω	40A/100 Ω	2000:1	10.00	101.00	28.00	50~60HZ
CT-136Z-3.0*3	200A/100 Ω	100A/100 Ω	3000:1	20.30	100.4	42.10	50~60HZ
CT-137Z-1.5*3	200A/100 Ω	100A/100 Ω	3000:1	20.30	100.4	42.10	50~60HZ
CT-138Z-2.0*3	200A/100 Ω	100A/100 Ω	2000:1	20.30	100.4	42.10	50~60HZ
CT-140-1.0	36A/100 Ω	20A/100 Ω	1000:1	11.50	31.00	16.00	0~200KHZ
CT-140-2.0	120A/100 Ω	60A/100 Ω	2000:1	11.50	31.00	16.00	0~200KHZ
CT-140Z-1.0	150A/100 Ω	100A/100 Ω	1000:1	11.50	31.00	16.00	50~60HZ
CT-140Z-2.0	300A/100 Ω	200A/100 Ω	2000:1	11.50	31.00	16.00	50~60HZ
CT-140Z-3.0	500A/100 Ω	300A/100 Ω	3000:1	11.50	31.00	16.00	50~60HZ
CT-141-0.02	30mA/1k Ω	30mA/1k Ω	20:1	16.00	38.00	14.50	0~200KHZ
CT-141Z-1.0	150A/100 Ω	100A/100 Ω	1000:1	14.50	38.20	17.00	50~60HZ
CT-141Z-2.0	600A/100 Ω	500A/100 Ω	2000:1	14.50	38.20	17.00	50~60HZ
CT-141Z-3.0	800A/100 Ω	600A/100 Ω	3000:1	14.50	38.20	17.00	50~60HZ
CT-142-2.0*3	55A/20 Ω	32A/20 Ω	2000:1	6.80	34.00	17.00	0~200KHZ
CT-143Z-1.0	270A/100 Ω	200A/100 Ω	1000:1	19.00	44.50	15.30	50~60HZ
CT-146-0.5	10A/10 Ω	5A/10 Ω	500:1	1.2*6	19.50	15.00	10K~70KHZ
CT-147-1.0*2	100A/100 Ω	40A/100 Ω	1000:1	9.55	58.00	33.50	50~60HZ
CT-148-2.0*2	400A/100 Ω	200A/100 Ω	2000:1	36.00	66.00	44.00	50~60HZ
CT-149-	100A/20 Ω	50A/20 Ω	250:1	40.00	25.00	15.00	0~200KHZ
0.95-0.5	50A/20 Ω	20A/20 Ω	500:1	40.00	25.00	15.00	0~200KHZ
CT-150V-0.5	30mA/1k Ω	30mA/1k Ω	500:1	10.38	24.2	11.50	0~200KHZ
CT-150H-0.5	30mA/1k Ω	30mA/1k Ω	500:1	10.38	24.2	11.50	0~200KHZ
CT-150H-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	10.38	24.2	11.50	0~200KHZ



contents

Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-151-0.5	30mA/1k Ω	30mA/1k Ω	500:1	12.70	28.50	12.30	0~200KHZ
CT-151Z-1.0	200A/100 Ω	100A/100 Ω	1000:1	12.70	28.50	12.30	50~60HZ
CT-151Z-2.0	250A/100 Ω	150A/100 Ω	2000:1	12.70	28.50	12.30	50~60HZ
CT-153-1.0	45A/100 Ω	32A/100 Ω	1000:1	14.50	30.50	15.56	0~200KHZ
CT-153-2.0	60A/100 Ω	40A/100 Ω	2000:1	14.50	30.50	15.56	0~200KHZ
CT-153Z-1.0	75A/100 Ω	50A/100 Ω	1000:1	14.50	30.50	15.56	50~60HZ
CT-153Z-2.0	200A/100 Ω	100A/100 Ω	2000:1	14.50	30.50	15.56	50~60HZ
CT-153Z-2.5	500A/100 Ω	200A/100 Ω	2500:1	14.50	30.50	15.56	50~60HZ
CT-160-0.5	30mA/1k Ω	60uA/100 Ω	500:1	6.2	16.8	7.2	0~200KHZ
CT-162-2.0	1500A/100 Ω	1000A/100 Ω	2000:1	45.00	75.70	24.50	0~200KHZ
CT-162-3.0	2000A/100 Ω	1200A/100 Ω	3000:1	45.00	75.70	24.50	0~200KHZ
CT-162-4.0	2500A/100 Ω	1500A/100 Ω	4000:1	45.00	75.70	24.50	0~200KHZ
CT-163Z-1.0	300A/100 Ω	200A/100 Ω	1000:1	23.50	56.60	23.50	50~60HZ
CT-163L-1.0	300A/100 Ω	200A/100 Ω	1000:1	23.50	56.60	23.50	50~60HZ
CT-172-2.0	120A/100 Ω	60A/100 Ω	2000:1	13.00	31.60	12.00	0~200KHZ
CT-179Z-0.715*2	1500A/100 Ω	1000A/100 Ω	715:2	33.70	59.00	20.00	50~60HZ
CT-182-2.0	105A/100 Ω	80A/100 Ω	2000:1	16.24	37.80	15.00	0~200KHZ
CT-183Z-2.0	800A/100 Ω	600A/100 Ω	2000:1	20.00	52.00	28.00	50~60HZ
CT-185-0.5	30mA/1k Ω	30mA/1k Ω	500:2	11.8	30.2	16.8	0~200kHZ
CT-189-2.0	2000A/100 Ω	1000A/100 Ω	2000:1	65.00	98.7	24.50	0~200KHZ
CT-194-2.0	190A/100 Ω	100A/100 Ω	2000:1	35.00	65.00	22.50	0~200KHZ
PT-190-1.0/1.0	1.0mA/1.0mA	1.0mA/1.0mA	1000:1000	18.2	20.0	10.0	0~200KHZ
CT-196-2.0	1500A/100 Ω	1000A/100 Ω	2000:1	44.00	71.50	20.00	0~200KHZ
CT-197Z-2.0	500A/100 Ω	300A/100 Ω	1000:1	32.80	46.50	15.20	50~60HZ
CT-201-0.5	30mA/1k Ω	60uA/100 Ω	500:1	6.5	18.2	7.3	0~200KHZ
CT-203F-2.0	112A/100 Ω	60A/100 Ω	2000:1	16.00	41.50	15.00	10~70KHZ
CT-203F-3.0	150A/100 Ω	80A/100 Ω	2000:1	16.00	41.50	15.00	10~70KHZ
CT-215-0.1	30mA/1K Ω /DC6mA	30mA/1k Ω	100:1	16.00	32.20	10.00	0~7KHZ
CT-215-0.5	30mA/1k Ω	30mA/1k Ω	500:1	16.00	32.20	10.00	0~200KHZ
CT-215-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	16.00	32.20	10.00	0~200KHZ
CT-215-2.0	30mA/1k Ω	30mA/1k Ω	2000:1	16.00	32.20	10.00	0~200KHZ
CT-215V-2.0	30mA/1k Ω	30mA/1k Ω	2000:1	16.00	32.20	10.00	0~200KHZ
CT-215H-2.0	30mA/1k Ω	30mA/1k Ω	2000:1	16.00	32.20	10.00	0~200KHZ



Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-222F-1.65	160A/47 Ω	100A/47 Ω	1650:1	16.00	46.00	17.60	10~70KHZ
CT-222F-2.0	110A/100 Ω	100A/100 Ω	2000:1	16.00	46.00	17.60	10~70KHZ
CT-222F-3.0	130A/100 Ω	100A/100 Ω	3000:1	16.00	46.00	17.60	10~70KHZ
CT-225Z-2.0	250A/100 Ω	200A/100 Ω	2000:1	40.8	57.30	14.56	50~60HZ
CT-225Z-4.0	500A/100 Ω	300A/100 Ω	4000:1	40.8	57.30	14.56	50~60HZ
CT-227Z-2.0	250A/100 Ω	200A/100 Ω	2000:1	58.90	74.5	14.40	50~60HZ
CT-228Z-4.0	500A/100 Ω	300A/100 Ω	4000:1	63.5	90.9	15.29	50~60HZ
CT-229Z-2.5	500A/100 Ω	300A/100 Ω	4000:1	40.0	90.0	29.00	50~60HZ
CT-237-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.00	30.00	12.00	0~200KHZ
CT-240	40A/100 Ω	32A/100 Ω	2000:1	2.50	41.50	21.00	0~200KHZ
2.0:	30mA/1k Ω	30mA/1k Ω	500:1	2.50	41.50	21.00	50~60HZ
1.0:1.0	1mA/1mA	1mA/1mA	1000:1000	2.50	41.50	21.00	0~200KHZ
CT-242-3.0	120A/100 Ω	100A/100 Ω	3000:1	25.7*9.5	44.5	15.50	10~70KHZ
CT-245-1:1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.1	32.50	22.50	0~200KHZ
CT-245B-0.01-0.2-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.1	32.50	22.50	0~200KHZ
CT-245C-0.02-0.2-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.1	32.50	22.50	0~200KHZ
CT-245E-0.02-0.2-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.1	32.50	22.50	0~200KHZ
CT-245F-2:1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.1	32.50	22.50	0~200KHZ
CT-245G-3:1.0	30mA/1k Ω	30mA/1k Ω	1000:1	14.1	32.50	22.50	0~200KHZ
CT-247-2.0	94A/100 Ω	50A/100 Ω	2000:1	11.70	29.00	16.35	0~200KHZ
CT-249F-1.0	220A/100 Ω	100A/100 Ω	1000:1	22.00	59.60	24.50	10~70KHZ
CT-249F-2.0	220A/100 Ω	150A/100 Ω	2000:1	22.00	59.60	24.50	10~70KHZ
CT-249F-3.0	300A/100 Ω	200A/100 Ω	3000:1	22.00	59.60	24.50	10~70KHZ
CT-255Z-3.0	150A/100 Ω	100A/100 Ω	3000:1	20.00	37.50	14.00	50~60HZ
CT-256-1.8	70A/50 Ω	32A/50 Ω	1800:1	4.00	20.00	13.00	0~200KHZ
CT-257F-3.0	300A/100 Ω	200A/100 Ω	3000:1	27.2	68.00	31.00	10~70KHZ
CT-259-2.0	120A/50 Ω	50A/50 Ω	2000:1	4.00	20.00	17.00	0~200KHZ
CT-260-1.0	30mA/1k Ω	30mA/1k Ω	1000:1	2.0	23.00	16.50	0~200KHZ
CT-281-0.5	30mA/1k Ω	30mA/1k Ω	500:1	3.00	21.40	20.2	0~200KHZ
CT-281-2.0	115A/50 Ω	50A/50 Ω	2000:1	3.00	21.40	20.2	0~200KHZ
CT-282F-2.0	300A/100 Ω	200A/100 Ω	2000:1	39.50	62.50	24.50	10~70KHZ
CT-282F-3.0	500A/100 Ω	300A/100 Ω	3000:1	39.50	62.50	24.50	10~70KHZ
CT-283Z-1.0	600A/100 Ω	300A/100 Ω	1000:1	13.00	40.00	14.00	50~60HZ
CT-283Z-3.0	800A/100 Ω	400A/100 Ω	3000:1	13.00	40.00	14.00	50~60HZ
CT-285Z-1.0 *2	100A/100 Ω	40A/100 Ω	1000:1	10.00	31.00	35.00	50~60HZ



contents

Product number	Maximum Current (A)	Rated current (A)	Ratio (TS)	Inner diameter (mm)	Outside Diameter (mm)	Thickness (mm)	Work frequency (HZ)
CT-290-0.1	30mA/DC6mA1kΩ	30mA/1kΩ	500:1	10.20	24.00	9.00	0~7KHZ
CT-291Z-4.0	950A/100Ω	400A/100Ω	4000:1	33.00	56.00	15.00	50~60HZ
CT-295F-2.0	30A/DC15A/50Ω	20A/50Ω	2000:1	4.0	24.50	15.50	0~200KHZ
CT-296-1.0	30mA/1kΩ	30mA/1kΩ	500:1	16.00	33.00	10.00	0~200KHZ
CT-301-2.0L	57A/50Ω	32A/50Ω	2000:1	8.60	16.14	15.00	0~200KHZ
CT-304-2.0	120A/50Ω	100A/50Ω	2000:1	21.0	40.2	40.2	0~200KHZ
CT-306-3:1.0	30mA/1kΩ	30mA/1kΩ	1000:1	20.00	39.00	11.50	0~200KHZ
CT-306H-0.1	30mA/DC6mA1kΩ	30mA/1kΩ	100:1	20.00	39.00	11.50	0~200KHZ
CT-306H-75:5:75	30mA/DC6mA1kΩ	30mA/1kΩ	75:5:75	20.00	39.00	11.50	0~200KHZ
CT-310Z-2.0*2	1000A/100Ω	400A/100Ω	2000:1	36.3	58.60	42.27	50~60HZ
CT-312-2.0L	36A/50Ω	32A/50Ω	2000:1	5.00	19.50	10.00	0~200KHZ
CT-313-1.0	30mA/1kΩ	30mA/1kΩ	500:1	20.00	33.00	11.00	0~200KHZ
CT-315-10:1.0	30mA/1kΩ	30mA/1kΩ	1000:1	2.5*10.5	41.00	22.00	0~200KHZ
CT-330-2.0L	100A/50Ω	50A/50Ω	2000:1	9.80	29.4	16.00	0~200KHZ
CT-331-2.0L	100A/50Ω	50A/50Ω	2000:1	13.8	33.4	17.00	0~200KHZ
CT-332-2.0L	80A/50Ω	40A/50Ω	2000:1	12.00	29.00	15.60	0~200KHZ
CT-333-2.0L	120A/50Ω	80A/50Ω	2000:1	2.5*10	37.60	21.00	0~200KHZ
CT-334-2.0L	36A/50Ω	32A/50Ω	2000:1	7.60	23.40	10.00	0~200KHZ
CT-336-2.0L	100A/50Ω	80A/50Ω	2000:1	14.5	35.5	17.00	0~200KHZ
CT-337-2.0L	150A/50Ω	120A/50Ω	2000:1	18.00	40.5	19.50	0~200KHZ
CT-338V-0.1	30mA/DC6mA1kΩ	30mA/1kΩ	100:1	15.6	35.5	15.0	0~200KHZ
CT-340Z-2.5*3	98A/100Ω	50A/100Ω	2500:1	9.40	24.00	11.70	50~60HZ
CT-341-2.0	90A/50Ω	40A/50Ω	2000:1	5.0	26.0	15.00	0~200KHZ
PT-342-1.0/1.0	2.0mA/2.0mA	2.0mA/2.0mA	1000:1000	17.0	20.2	27.10	0~200KHZ
CT-343-2.0	120A/50Ω	60A/50Ω	2000:1	9.8	29.9	16.00	0~200KHZ
CT-344-2.0	90A/50Ω	40A/50Ω	2000:1	8.0	29.0	14.0	0~200KHZ
CT-345-2.0	90A/100Ω	60A/100Ω	2000:1	12.0	29.0	15.6	0~200KHZ
CT-346-2.0	120A/100Ω	80A/100Ω	2000:1	13.8	33.4	17.0	0~200KHZ
CT-361	200A/50Ω	100A/50Ω	2.5/1.0/0.5/0.02/0.1	11.50	64.50	30.50	0~200KHZ
CT-504-1.0	50A/50Ω	32A/50Ω	1000:1	1.0	29.00	14.9	10~70KHZ
CTK-Φ10-1.0	20A/50Ω	10A/50Ω	1000:1	10.00	40.2	27.00	0~200KHZ
CTK-Φ16-2.0	120A/50Ω	80A/50Ω	2000:1	16.00	47.5	31.8	0~200KHZ
CTK-Φ24-3.0	300A/50Ω	200A/50Ω	3000:1	24.00	71.00	44.00	50~60HZ
CTK-Φ36-5.0	500A/50Ω	40A/50Ω	5000:1	36.00	87.00	55.00	50~60HZ